


POLE LENGTH H	PLANTING DEPTH D	POLE SIZES TO BE USED AS FOLLOWS:
7m	1.0m	SERVICE CONNECTION KICK POLES LV RETICULATION LINES, LV RETICULATION LINES, IN VILLAGES FOR BACKBONE 33kV LINE ACCOMMODATING ORGW FOR LOTB AND GW FOR LOT A FOR ALL ROAD CROSSINGS.
8m	1.2m	
9m	1.5m	
11m	1.5m	
12m	2.0m	
13m	2.0m	

COPYRIGHT © 2009 EMCON
 ALL RIGHTS RESERVED. NO PART OF THIS PUBLICATION MAY BE REPRODUCED STORED IN A RETRIEVAL SYSTEM OR TRANSMITTED IN ANY FORM OR BY ANY MEANS, INCLUDING PHOTOCOPYING, RECORDING OR OTHERWISE, WITHOUT THE PERMISSION IN WRITING FROM EMCON.

ITEM	DESCRIPTION	QTY	REMARKS
1	POLE CAP		
2	1.2m DANGER PLATE		
3	M20 EYEBOLT ASSEMBLY		
4	INSULATOR		
5	M16 PIGTAIL BOLT ASSEMBLY		

- NOTES:**
1. POLES TO BE PLANTED AT MINIMUM DEPTHS AS SHOWN IN THE TABLE.
 2. POLES SHALL BE PLANTED VERTICALLY PLUMB AND IN LINE AND SUFFICIENTLY STAYED TO MAINTAIN THAT POSITION.
 3. THE POLE EARTH CONDUCTOR SHALL BE STAPLED TO THE POLE AT 500mm C/C AND TERMINATED ON THE EYEBOLT OR PIGTAIL BOLT BETWEEN FISHPATE AND POLE.

ELECTRICITY CONTROL BOARD



Box 2923
 Windhoek
 NAMIBIA
 Tel: (061) 374300
 Fax: (061) 374305

DRAWING TITLE
 MEDIUM VOLTAGE BARE OVERHEAD DISTRIBUTION
 POLE PLANTING DETAIL

DESIGNED: A.K	DRAWN: J.W.S	REV: 01-2001
DRAWING No: STD-DM/VAE-33kV-15	SCALE: N.T.S	

ERROR: syntaxerror
OFFENDING COMMAND: --nostringval--

STACK:

/Title
()
/Subject
(D:20100127125420+02'00')
/ModDate
()
/Keywords
(PDFCreator Version 0.9.5)
/Creator
(D:20100127125420+02'00')
/CreationDate
(johnny)
/Author
-mark-